

## FEATURES

- ◆ Available as 2-or 3-axis machine controller
- ◆ Remote START / STOP / RESET
- ◆ Bidirectional serial communication at up to 19200 baud
- ◆ 32K of on-board memory, capable of holding over 1200 3-axis motions
- ◆ Built-in forced-air ventilation for continuous duty
- ◆ Screw terminal connectors on rear panel for easy I/O hook-up
- ◆ Can be programmed with removable memory module
- ◆ LED status display on front panel
- ◆ Commands can be executed as a "batch program" or each command can be executed in a command-by-command basis
- ◆ All power supplies are built-in & wired up
  - Motor - 44V / 4.3A for each axis
  - Logic - 5V / 1.5A
- ◆ Comes fully assembled & **READY TO USE**



## MOTION CAPABILITIES

- Linear interpolation on any 2 axes (XY, XZ or YZ) at rates up to 10K steps / sec.
- Motions up to  $\pm 8,000,000$  steps
- Switch-settable acceleration
- Can be programmed in both incremental & absolute coordinates

## INPUTS / OUTPUTS

- 8 optically isolated inputs up to 24V
- 8 optically isolated outputs up to 50V / 500 mA
- 8 open collector outputs up to 50V / 500 mA

## STEPPER AMPLIFIERS

- Each Stepper Motor Amplifier (model HL1100M313202) can produce up to 3.6A at 44V
- Total fault protection against:
  - Short circuit across phases
  - Short circuit to ground
  - Over / under voltage
  - Overtemperature

**NOTE:** This controller is **CE** compliant.

## APPLICATIONS

This controller is suitable for normal-duty applications. It is suitable for driving slides and gantries up to 500 mm in travel length with Z-axis loads of 25 lb. maximum. Note that since the motors will be powered with 3.3 A/phase, they will produce only 80% of their rated torque.

### The C116 Machine Controller consists of:

- 1 C116 enclosure
- 2 or 3 stepper drivers, HL1100M313202
- 1 Interface card 4.0 I/O, HL1200M325500
- 1 serial computer cable, HL1700M2784
- 2 or 3 motor cables, HX1700M6143

Catalog Number	Part Description	Dimensions	Weight lbs
HL1300MC116	C116 3-Axis Controller	20.3" x 11" x 6.7"	26.4
HL1300MC116-2	C116 2-Axis Controller		24

**NOTE:** The C116 3- and 2-axis controllers come complete with all power supplies, amplifiers, motor cables and serial cable to computer.

## ACCESSORIES

Catalog Number	Part Description
HL1100M313202	Stepper Motor Amplifier Card
HX1700M6143	10 ft. Motor Cable
H25Z61-DS1235AB	Battery-backed Memory

For memory card and additional accessories, see page 166.

## SOFTWARE OPTIONS

- PAL - English like language programming system (included).
- ASCII - Can be directly programmed through any communication program.
- Can be programmed via many third-party software packages.

(Back Panel of C116)

